EUROTEC
TECNOLOGIE IMPIANTISTICHE - AUTOMAZIONE - TELECONTROLLO

LUMEL
EVERYTHING COUNTS

NC12

AC/DC CLAMP-ON METER 1000 A/ 300 A

Unique Design

NC12 is a highly innovative design for features those increases **safety** and **comfort** of user.

- Rotating clamp jaws facilitate the measurement at physically awkward positions, vertical bus bars, conductors placed at positions difficult to access.
- Clamp jaws can be opened or closed with the trigger placed at bottom side away from the jaws. This allows the user to place his/her hand at safer distance from live conductor. This greatly reduces exposure of human beings to electrical shocks
- Location and design of trigger eliminates fatigues caused by single finger operation. It allows spreading the force required to open the jaws over more than one finger to ensure comfortable operation.
- Comfortable operation of push buttons and function selector switch, in adverse field conditions.

Application

NC12 measures important electrical parameters like AC Current, DC Current, AC Voltage, and DC Voltage. It also features Capacitance, Ohm & Continuity, frequency, and Duty cycle and temperature measurement.

Large Jaw Opening

For NC12 1000A AC-DC Jaw opening of 51mm for standard wire diameter of 50mm and for NC12 300A AC-DC Jaw opening of 41mm for standard wire diameter of 40mm for 300A

Narrow Body

Narrow housing for firm grip and easy to carry.

High Accuracy for low current measurement

The clamp meter can measure accurately at not only the High currents but also Low current ranges.

User selectable Backlit : (Optional)

It is possible to conduct measurement using the clamp meter during night time in darkness with the help of Backlit. The back lit can be switched ON or OFF by pressing a single key.

Temperature measurement

Temperatures from -200 to 800 °C using Pt 100 and Pt 1000 sensors.

AUTO POWER OFF

In order to save the power of the Batteries, the clamp meter will automatically shut OFF if it detects no activity for 10 minutes.

Analog Scale

Analog scale that updates at the rate 20 times/sec to observe fluctuations in input.

CONTINOUS ON MODE

In this mode, AUTO POWER OFF is disabled.

DATA Hold Function

By pressing DATA HOLD button, reading on the display can be latched for Hands free operation.

MIN,MAX Function

By pressing MIN/MAX button, the clamp meter will start recording latest Minimum and Maximum readings

NULL ZERO Correction for Resistance

For Low ohm measurement, the lead resistance can be compensated by pressing the shift key (Yellow Key)

NULL ZERO Correction for Capacitance

Null zero connection for capacitance. For nF range, stray capacitance can be compensated by shift key (Yellow Key)

AUTO and MANUAL ranging modes

In AUTO ranging mode the instrument automatically selects the range with best resolution depending on the applied input.
In MANUAL ranging mode range is user selectable using MAN key.

Diode Measurement

For testing diode and transistors, diode measurement function is available.

Protection from dust and water

IP20 for terminals as per EN 60529

Applicable International Safety standards

600 V CAT IV/1000V CAT III as per International Safety standard EN 61010-1

Double molded Cover for soft touch and firm grip of the Instrument

Measuring function	Measuring range	Resolution	Input impedance	Intrinsic error of digital display ± (…% of rdg + …digit) at reference condition	Over load capacity [1]	
					Over load value	Overload duration
V dc	30.00 mV	10 µV	>10 GΩ // <40pF	0.5 + 3 [2]	1000 V DC AC eff / rms Sine wave	Continuously
	300.0 mV	100 µV	>10 GΩ // <40pF	0.5 + 3		
	3.000 V	1 mV	11 MΩ // <40pF	0.25 + 1		
	30.00 V	10 mV	10 MΩ // <40pF	0.25 + 1		
	300.0 V	100 mV	10 MΩ // <40pF	0.25 + 1		
	1000 V	1 V	10 MΩ // <40pF	0.35 + 1		
V ~	3.000 V	1 mV	11 MΩ // <40pF	0.75 + 2 (10….300 Digit) 0.75 + 1 > 300 Digit		
	30.00 V	10 mV	10 MΩ // <40pF			
	300.0 V	100 mV	10 MΩ // <40pF			
	1000 V	1V	10 MΩ // <40pF			
Ω			**No load voltage**			
	30.00 Ω	10 mΩ	Max. 3.2 V	0.5 + 3 [2]	1000 V DC AC eff / RMS Sine wave	10 min
	300.0 Ω	100 mΩ	Max. 3.2 V	0.5 + 3		
	3.000 k Ω	1Ω	Max. 1.25 V	0.4 + 1		
	30.00 k Ω	10 Ω	Max. 1.25 V	0.4 + 1		
	300.0 k Ω	100 Ω	Max. 1.25 V	0.4 + 1		
	3.000 MΩ	1 k Ω	Max. 1.25 V	0.6 + 1		
	30.00 MΩ	10 k Ω	Max. 1.25 V	2.0 + 1		
⊣▶⊢	2.000 V	1 mV	Max. 3.2 V	0.25 + 1		
NC12 1000A~/ Adc	2 to 300.0 A	0.1 A	-----	1.5 % of range + 5 Digits	1100 A	Continuously
	1000 A	1 A	-----			
NC12 300A~/Adc	0.2 to 30.0A	0.01A	-----			
	300.0A	0.1 A	-----			

Measuring Function	Measuring range		Resolution	Discharge resistance	U_0 max.	Intrinsic error of digital display ± (…% of rdg + …digit) at reference condition	Over load capacity [1]	
							Over load value	Over load duration
F	30.00 nF		10 pF	250 kΩ	2.5 V	1.0 + 3 [2]	1000 V DC AC eff / rms Sine	10 min
	300.0 nF		100 pF	250 kΩ	2.5 V	1.0 + 3		
	3.000 µF		1 nF	25 kΩ	2.5 V	1.0 + 3		
	30.00 µF		10 nF	25 kΩ	2.5 V	3.0 + 3		
				f min V dc	**f min V ~**			
Hz	300.0 Hz		0.1 Hz	1 Hz	45 Hz	0.5 + 1 [3]	3 kHz 1000 v 30 kHz; 300 V 100 kHz 30 V	Continuously
	3.000 k Hz		1 Hz	1 Hz	45 Hz			
	30.00 k Hz		10 Hz	10 Hz	45 Hz			
	100.0 k Hz		100 Hz	100 Hz	100 Hz			
%	2.0....98.0%		0.1 %	2 Hz	-	2 Hz… 1kHz ± 5 Digit [4] 1 kHz … 10 kHz; ± 5 Digit / kHz [4]		
°C	Pt 100	-200.0... +200.0 °C	0.1 °C	-	-	2 Kelvin + 5 Digit [5]	1000 V DC AC eff / rms Sine	10 min
		+200.0... +850.0 °C	0.1 °C			1.0 + 5 [5]		
	Pt 1000	-100.0... +200.0 °C	0.1 °C	-	-	2 Kelvin + 2 Digit [5]		
		+200.0... +850.0 °C	0.1 °C			1.0 + 2 [5]		

1) At 0º …. + 40 ºC

2) With zero adjustment, without zero adjustment + 35 digits

3) Range :
   3 V ac/dc: Ue = 1.5 V eff/rms … 100 V eff/rms
   30 V ac/dc: Ue = 15 V eff/rms … 300 V eff/rms
   300 V ac/dc: Ue = 150 V eff/rms … 1000 V eff/rms

4) On the range 3 V dc, square – wave signal positive on one side 5 … 15 V, f = const., not 163.84 Hz or integral multiple.

5) Without sensor

Reference conditions for Accuracy

Reference temperature	23°C ± 2
Relative Humidity	45%...55% RH
Waveform of measured quantity	Sinusoidal
Input frequency	50 or 60 Hz ±2%
Battery Voltage	8 V ± 0.1 V

Environmental

Operating temperature	-10 to +55°C
Storage temperature	-20 to +70°C
Relative humidity	0... 90% non condensing
Terminal Protection	IP50 for Housing and IP20 for terminals

Battery

Battery Voltage	9 V DC
Battery type	Manganese Dioxide Cell as per IEC6F22 , alkaline manganese cell as per IEC 6LR 61
Battery Life	Minimum 220 hours on V DC, A DC, 80 hours on V AC, A AC

Display

Number of digits	3 ¾ digits.
Maximum count	3100 counts.
Over range indication	"OL" is displayed.
Polarity indication	"—" sign is displayed for DC functions, if positive pole is at"⊥".

Influence Quantities and Variations

Influence Quantity	Range of Influence	Measured Quantity/ Measuring Range		Variation [1] ± (….% of rdg. + ….digits)
Temperature	0 ºC +21 ºC and +25 ºC…+40ºC	30/300 mV dc		1.0 + 3
		3...300 V dc		0.15 + 1
		1000 V dc		0.2 + 1
		V ~		0.4 + 2
		30 Ω [2]		0.15 + 2
		300 Ω		0.25 + 2
		3 kΩ – 3 MΩ		0.15 + 1
		30 MΩ		1.0 + 1
		30 nF [2] – 3 µF		0.5 + 2
		30 µF		2.0 + 2
		Hz		0.5 + 1
		%		± 5 digits
		-200…+200 ºC		0.5 K + 2
		+200…+850ºC		0.5 + 2
		NC121000A AC-DC	30 A ~/ A DC	0.2 X Specified accuracy
			300 A ~/ A DC	0.1 X Specified accuracy
		NC12300A AC-DC	300 A ~/ A DC	0.2 X Specified accuracy
			1000 A ~/ A DC	0.1 X Specified accuracy
Frequency of the measured quantity	> 65 Hz...400 Hz	3…300 V ~		2.0 + 3
	>400 Hz…1 KHz			
	>65 Hz … 1 KHz	1000 V ~		3.0 + 3
	15Hz …<45 Hz	A ~		1.0 % of range + 1
	>66 Hz… 400 Hz			

NC12- AC/DC CLAMP-ON METER 1000 A/ 300 A

LUMEL
EVERYTHING COUNTS

Influence Quantity	Range of Influence		Measured Quantity/ Measuring Range	Variation [1] ± (….% of rdg. + ….digits)
Wave form of the measured quantity [3]	Crest factor CF	1....3	V ~ [4] A ~ [4]	± 1 % of rdg
		1....5		± 3 % of rdg
Battery Voltage	[5] …< 7.9 V > 8.1 V …10.0 V		V DC	2 Digit
			V~	4 Digit
			AAC/ADC	8 Digit
			30Ω / 300 Ω/°C	4 Digit
			3 kΩ – 30MΩ	3 Digit
			nF, µF	10 Digit
			Hz	10 Digit
			%	10 Digit
Relative humidity	75% 3 Days Meter off		V~,VDC A~, ADC Ω F Hz % °C	1 x intrinsic error
HOLD	-		--	± 1 digits
MIN/MAX	-		V AC/DC , A ~ , A DC	± 2 digits

1) With temperature: Error data apply per 10 K change in temperature.
For Aac/Adc error data apply per K change in temperature.
With frequency: Error data apply to a display from 300 digits onwards.
2) With zero adjustment.
3) With unknown waveform (crest factor CF > 2), measure with manual range selection
4) With the exception of sinusoidal waveform.
5) After the " " symbol is displayed

Applicable Standards

EMC	Electro magnetic compatibility
Emission	EN 61000-6-4
Immunity	EN 61000-6-2
	8 kV atmosphere discharge, 4 kV contact discharge EN 61000-4-3 : 3 V/m

Safety

	EN 61010-1-2010
IP for water & dust	EN 60529
Pollution degree	2
Installation category	IV
High Voltage Test	6.7 kV AC, 50Hz for 1 minute between housing and input. 3.7 kV AC, 50Hz for 1 minute between housing with jaws and input.

Weight

0.6 kg

Warranty

1 year

ORDERING CODE

Clamp meter NC12 -	X	XX	X	X
Maximal range of current measurement a.c./d.c.:				
300 A	1			
1000 A	2			
Version:				
standard		00		
custom-made*		XX		
Language:				
Polish			P	
English			E	
other*			X	
Acceptance tests:				
with an extra quality inspection certificate				1
with test certificate				2
acc. to custromer's request				X

* after agreeing with the manufacturer

ITEMS AVAILABLE FROM OUR STOCK:

NC12 - 100E1
version: 300A

NC12 - 200E1
version: 1000A

Via Lirone 60/i, Castel Maggiore (BO) 40013
e-mail: info@eurotecsrl.com Website: www.eurotecsrl.com
Tel: +39 051/6321595 C.F. 04103780377 P.I. 01596581205